



Release Notes

FortiAnalyzer 7.6.7



FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO LIBRARY

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/training-certification>

FORTINET TRAINING INSTITUTE

<https://training.fortinet.com>

FORTIGUARD LABS

<https://www.fortiguard.com>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdoc@fortinet.com



June 15, 2026

FortiAnalyzer 7.6.7 Release Notes

05-767-1296363-20260615

TABLE OF CONTENTS

Change Log	6
FortiAnalyzer 7.6.7 Release	7
Supported models	7
Special branch supported models	7
FortiAnalyzer VM subscription license	8
Special Notices	9
FortiCare Elite or FortiCare Premium required to download FortiGuard objects	9
FortiAnalyzer instances deployed on the Azure platform	9
The FortiAnalyzer XML API is no longer supported	10
legacy-auth-mode command added	10
The grep command is added to the CLI	10
FortiManager Connector	11
Default password policy for local users	11
Quotations applied to fields containing string-type data	11
MEAs removed in FortiAnalyzer 7.6.3	11
Migrating the log database from Postgres to ClickHouse	11
Shell access has been removed	12
Alert notifications generated by FortiAnalyzer and sent by syslog	12
Additional configuration required for SSO users	12
FortiAnalyzer 7.2.3 and later firmware on FortiGuard	12
Configuration backup requires a password	13
FortiAnalyzer-3500E support	13
Serial console has changed for FortiAnalyzer deployments on Xen	14
OpenXen in PV mode is not supported in FortiAnalyzer 7.4.1	14
Default GUI theme changed	14
FortiManager Features removed	14
Setup wizard requires FortiCare registration	14
Hyperscale firewall mode	15
Modifying the interface status with the CLI	15
Citrix XenServer default limits and upgrade	15
FortiAnalyzer VM upgrade requires more memory	16
Maximum ADOM limits for FortiAnalyzer	16
Port 8443 reserved	16
Hyper-V FortiAnalyzer-VM running on an AMD CPU	17
SSLv3 on FortiAnalyzer-VM64-AWS	17
New features	18
Upgrade Information	19
Downgrading to previous firmware versions	19
Firmware image checksums	19
FortiAnalyzer VM firmware	19
SNMP MIB files	21

Product Integration and Support	22
Supported software	22
Web browsers	23
FortiOS and FortiOS Carrier	23
FortiADC	23
FortiNDR	24
FortiAnalyzer	24
FortiAP	24
FortiAuthenticator	25
FortiCache	25
FortiCASB	25
FortiClient	25
FortiDDoS	26
FortiDeceptor	26
FortiFirewall and FortiFirewallCarrier	26
FortiIsolator	26
FortiMail	27
FortiManager	27
FortiNAC	27
FortiPAM	27
FortiPortal	28
FortiProxy	28
FortiSandbox	28
FortiSASE	28
FortiSOAR	28
FortiSRA	29
FortiSwitch ATCA	29
FortiToken	29
FortiWeb	29
Virtualization	29
Feature support	30
Language support	31
Supported models	32
FortiGate models	33
FortiGate special branch models	40
FortiCarrier models	44
FortiCarrier special branch models	47
FortiADC models	49
FortiNDR models	50
FortiAnalyzer models	50
FortiAP models	51
FortiAuthenticator models	52
FortiCache models	53
FortiDDoS models	53
FortiDeceptor models	53
FortiFirewall models	54
FortiFirewallCarrier models	55
FortiIsolator models	56
FortiMail models	56

FortiNAC models	56
FortiPAM models	57
FortiProxy models	57
FortiSandbox models	58
FortiSOAR models	58
FortiSRA models	59
FortiSwitch ATCA models	59
FortiWeb models	59
Resolved issues	61
Device Manager	61
Event Management	61
Log View	61
Others	61
Reports	62
System Settings	62
Known issues	63
New known issues	63
Existing known issues	63
Fabric View	63
FortiSoC	63
FortiView	64
Others	64
Reports	64
System Settings	64
Appendix A - Default and maximum number of ADOMs supported	65
Hardware models	65
Virtual Machines	66

Change Log

Date	Change Description
2026-06-02	Initial release of 7.6.7.
2026-06-04	Updated Supported models on page 7
2026-06-15	Updated FortiProxy on page 28 .

FortiAnalyzer 7.6.7 Release

This document provides information about FortiAnalyzer version 7.6.7 build 3737.



The recommended minimum screen resolution for the FortiAnalyzer GUI is 1920 x 1080. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

This section includes the following topics:

- [Supported models on page 7](#)
- [FortiAnalyzer VM subscription license on page 8](#)

Supported models

FortiAnalyzer version 7.6.7 supports the following models:

FortiAnalyzer	FAZ-300G, FAZ-800G, FAZ-810G, FAZ-1000F, FAZ-1000G, FAZ-2000E, FAZ-3000F, FAZ-3000G, FAZ-3100G, FAZ-3500F, FAZ-3500G, FAZ-3510G, FAZ-3700F, and FAZ-3700G, FAZ-3750G.
FortiAnalyzer VM	FAZ_VM64, FAZ_VM64_ALI, FAZ_VM64_AWS, FAZ_VM64_AWSOnDemand, FAZ_VM64_Azure, FAZ_VM64_GCP, FAZ_VM64_HV (including Hyper-V 2016, 2019, and 2022), FAZ_VM64_IBM, FAZ_VM64_KVM, FAZ_VM64_OPC, FAZ_VM64_XEN (for both Citrix and Open Source Xen).

Special branch supported models

The following models are released on a special branch of FortiAnalyzer 7.6.7. To confirm that you are running the correct build, run the CLI command `get system status` and check that the `Branch point` field shows 3737.

FAZ_150G	is released on build 6180.
-----------------	----------------------------



For access to container versions of FortiAnalyzer, contact [Fortinet Support](#).

FortiAnalyzer VM subscription license

The FortiAnalyzer VM subscription license supports FortiAnalyzer version 6.4.1 and later. For information about supported firmware, see [FortiAnalyzer VM firmware on page 19](#).

See also [Appendix A - Default and maximum number of ADOMs supported on page 65](#).



You can use the FortiAnalyzer VM subscription license with new FortiAnalyzer-VM installations.

For existing FortiAnalyzer-VM installations, you can migrate to a FortiAnalyzer VM subscription license, starting with FortiAnalyzer 7.0.1. See the [FortiAnalyzer Administration Guide](#).

Special Notices

This section highlights some of the operational changes that administrators should be aware of in FortiAnalyzer version 7.6.7.

FortiCare Elite or FortiCare Premium required to download FortiGuard objects

Starting in 7.2.12, 7.4.9, and 7.6.5, FortiAnalyzer requires a valid FortiCare Elite or FortiCare Premium support contract registered in FortiCloud in order to get object updates from FortiGuard.

FortiAnalyzer instances deployed on the Azure platform

FortiAnalyzer instances deployed on the Azure platform (regardless of version) may lose all data—including configuration, logs, and reports—if the VM is deallocated and subsequently reallocated.

This issue can occur when the VM is deallocated through Azure-level operations (e.g., Azure portal, CLI, or automation). For example, this may happen when an Azure administrator changes the VM SKU (e.g., from Standard_D16_v3 to Standard_D32a_v4), or when the VM is manually stopped (deallocated) from the Azure portal.

To minimize the risk of data loss, it is strongly recommended to:

- Perform regular backups of configuration and data via the GUI or native CLI commands on FortiAnalyzer.
- Shut down the FortiAnalyzer instance, if required, only from within the FortiAnalyzer system itself rather than through Azure-level controls.
- Before performing any upgrade or modification:

Run `execute lvm info` to verify disk composition and ensure no Azure temporary disk is included in LVM, For example:

Disk 1: 10 TB, Disk 2: 6 TB, ...

If all listed disks were explicitly added by the `faz-admin`, this indicates that no temporary disk is part of LVM and the upgrade is considered safe.

If an unexpected disk is detected (e.g., smaller system disk such as ~128 GB), it is likely the Azure temporary disk. In this case, perform a full backup before proceeding with the upgrade.

If issues occur after the upgrade:

- Run `execute format disk` to rebuild LVM,
- Use `execute restore` to recover data from backup.

The possible root cause may be as follows:

Prior to version 7.4.2, the system assumed `sdb` was always the Azure temporary disk and excluded it from LVM. In certain corner cases, a different device (e.g., `sda`) may have been incorrectly added to LVM. After upgrading, the existing LVM metadata persists on disk. When the VM is later deallocated and reallocated, Azure replaces the temporary disk, causing LVM initialization to fail due to stale metadata. As a result, any data previously stored on the temporary disk is lost.

The FortiAnalyzer XML API is no longer supported

The XML API is removed as of FortiAnalyzer 7.6.5.

legacy-auth-mode command added

A new CLI command, `legacy-auth-mode`, has been introduced to enhance the flexibility of OFTP connections between devices and FortiAnalyzer when needed. By default, FortiAnalyzer enforces certificate-based authentication for OFTP connections and validates the device's certificate by checking the Common Name (CN) field — if the CN matches the device's serial number (SN), the connection is accepted.

However, for devices like FortiWeb, FortiMail, and FortiADC, the certificate CN often does not match the SN, causing the OFTP connection to fail. When `legacy-auth-mode` is enabled, FortiAnalyzer allows OFTP connections to fall back to username/password authentication if the certificate CN does not match the SN. This enables compatibility with devices whose certificates use alternative CN formats while still providing a level of authentication. In line with security best practices, the OFTP port should not be exposed when `legacy-auth-mode` is enabled unless proper access restrictions are applied.

```
config system log settings
(settings)# set legacy-auth-mode ?
    disable - Disable support for legacy authentication mode.
    enable - Enable support for legacy authentication mode.
```

The grep command is added to the CLI

The `grep` command is added in FortiAnalyzer 7.6.5 CLI. This command can be used to filter larger outputs so that they only show the required information.

For more information, see the [FortiAnalyzer CLI Reference](#).

FortiManager Connector

In FortiAnalyzer 7.6.4, the FMG Connector is moved to *Incidents & Events > Automation > Active Connectors*.

Default password policy for local users

Beginning in FortiAnalyzer 7.6.4, a password policy for local users is enabled and configured by default. If you are setting up FortiAnalyzer 7.6.4 or later, the password created at setup must be at least 8 characters and must contain uppercase letter(s), lowercase letter(s), number(s), and special character(s).

Note that existing password policy settings are maintained after upgrading. For example, if the password policy is disabled prior to upgrading to FortiAnalyzer 7.6.4 or later, it will remain disabled after the upgrade.

Quotations applied to fields containing string-type data

Starting from version 7.6.3, quotations are consistently applied to the fields containing string-type data. For example: srcip, dstip, transip, date, and time.

MEAs removed in FortiAnalyzer 7.6.3

There is no support for MEAs in FortiAnalyzer 7.6.3 and later.

The following management extension applications (MEAs) are removed in FortiAnalyzer 7.6.3:

- FortiSIEM
- FortiSOAR

Migrating the log database from Postgres to ClickHouse

Beginning in FortiAnalyzer 7.6.0, FortiAnalyzer stores logs in a ClickHouse SQL database rather than a Postgres SQL database.

For more information, see the [FortiAnalyzer 7.6.0 Upgrade Guide](#).

Shell access has been removed

As of FortiAnalyzer 7.6.0, shell access has been removed.

The following CLI variables have been removed, which were previously used to enable shell access:

```
config system admin setting
    set shell-access {enable | disable}
    set shell-password <passwd>
```

The following CLI command has been removed, which was previously used to access shell when enabled:

```
execute shell
```

Alert notifications generated by FortiAnalyzer and sent by syslog

Beginning in 7.4.3, alert notifications generated by FortiAnalyzer and sent by syslog will use the RFC-5424 format.

Additional configuration required for SSO users

Beginning in 7.4.3, additional configuration is needed for FortiAnalyzer Users declared as wildcard SSO users.

When configuring Administrators as wildcard SSO users, the `ext-auth-acprofile-override` and/or `ext-auth-adom-override` features, under *Advanced Options*, should be enabled if the intent is to obtain the ADOMs list and/or permission profile from the SAML IdP.

FortiAnalyzer 7.2.3 and later firmware on FortiGuard

Starting in FortiAnalyzer 7.2.1, a setup wizard executes to prompt the user for various configuration steps and registration with FortiCare. During the execution, the FortiAnalyzer unit attempts to communicate with FortiGuard for a list of FortiAnalyzer firmware images currently available on FortiGuard – older and newer.

In the case of FortiAnalyzer 7.2.2, a bug in the GUI prevents the wizard from completing and prevents the user from accessing the FortiAnalyzer unit. The issue has been fixed in 7.2.3 and later and a CLI command has been added to bypass the setup wizard at login time.

```
config system admin setting
    set firmware-upgrade-check disable
```

end

Fortinet has not uploaded FortiAnalyzer 7.2.3 and later firmware to FortiGuard in order to work around the GUI bug, however, the firmware is available for download from the [Fortinet Support website](#).

Configuration backup requires a password

As of FortiAnalyzer 7.4.2, configuration backup files are automatically encrypted and require you to set a password. The password is required for scheduled backups as well.

In previous versions, the encryption and password were optional.

For more information, see the [FortiAnalyzer Administration Guide](#).

FortiAnalyzer-3500E support

FortiAnalyzer 7.4.2 and later does not support the FortiAnalyzer-3500E device.

FortiAnalyzer 7.4.2 introduces an upgrade of the OpenSSL library to address known vulnerabilities in the library. As a result, the SSL connection that is setup between the FortiAnalyzer-3500E device and the Google Map server hosted by Fortinet uses a SHA2 (2048) public key length. The certificate stored on the BIOS that is used during the setup of the SSL connection contains a SHA1 public key length, which causes the connection setup to fail. Running the following command shows the key length.

```
FAZ3500E # config system certificate local
(local)# ed Fortinet_Local
(Fortinet_Local)# get
  name : Fortinet_Local
  password : *
  comment : Default local certificate
  private-key :
  certificate :
  Subject: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = FortiAnalyzer, CN =
    FL3K5E3M15000074, emailAddress = support@fortinet.com
  Issuer: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = Certificate Authority,
    CN = support, emailAddress = support@fortinet.com
  Valid from: 2015-03-06 16:22:10 GMT
  Valid to: 2038-01-19 03:14:07 GMT
  Fingerprint: FC:D0:0C:8D:DC:57:B6:16:58:DF:90:22:77:6F:2C:1B
  Public key: rsaEncryption (1024 bits)
  Signature: sha1WithRSAEncryption
  Root CA: No
  Version: 3
  Serial Num:
  1e:07:7a
  Extension 1: X509v3 Basic Constraints:
  CA:FALSE
  ...
(Fortinet_Local)#
```

Serial console has changed for FortiAnalyzer deployments on Xen

In FortiAnalyzer 7.4.1, the serial console for Xen deployments has changed from hvc0 (Xen specific) to ttyS0 (standard).

OpenXen in PV mode is not supported in FortiAnalyzer 7.4.1

As of FortiAnalyzer 7.4.1, kernel and rootfs are encrypted. OpenXen in PV mode tries to unzip the kernel and rootfs, but it will fail. Therefore, OpenXen in PV mode cannot be used when deploying or upgrading to FortiAnalyzer 7.4.1. Only HVM (hardware virtual machine) mode is supported for OpenXen in FortiAnalyzer 7.4.1.

Default GUI theme changed

As of FortiAnalyzer 7.4.1, the default GUI theme is *Jade*. The default theme can be changed from *System Settings > Settings*.

FortiManager Features removed

FortiAnalyzer 7.2.1 and later no longer supports FortiManager Features. If you have FortiManager Features enabled before upgrading to FortiAnalyzer 7.2.1, FortiManager Features will be permanently disabled after upgrading to FortiAnalyzer 7.2.1.

Setup wizard requires FortiCare registration

Starting in FortiAnalyzer 7.2.1, the FortiAnalyzer Setup wizard requires you to complete the *Register with FortiCare* step before you can access the FortiAnalyzer appliance or VM. Previously the step was optional.

For FortiAnalyzer units operating in a closed environment, contact customer service to receive an entitlement file, and then load the entitlement file to FortiAnalyzer by using the CLI.

When FortiManager is managing FortiAnalyzer in a closed environment, FortiManager contains the FortiAnalyzer contract information, and you can point FortiAnalyzer to FortiManager.

Hyperscale firewall mode

FortiAnalyzer does not support logs from the following models when they have hyperscale firewall mode and netflow enabled:

- FortiGate-1800F
- FortiGate-1801F
- FortiGate-2600F
- FortiGate-2601F
- FortiGate-4200F
- FortiGate-4201F
- FortiGate-4400F
- FortiGate-4401F

FortiAnalyzer only supports logs when the normal firewall mode with standard FortiGate logging are enabled.

Modifying the interface status with the CLI

Starting in version 7.0.1, the CLI to modify the interface status has been changed from up/down to enable/disable.

For example:

```
config system interface
  edit port2
    set status <enable/disable>
  next
end
```

Citrix XenServer default limits and upgrade

Citrix XenServer limits ramdisk to 128M by default. However the FAZ-VM64-XEN image is larger than 128M. Before updating to FortiAnalyzer 6.4, increase the size of the ramdisk setting on Citrix XenServer.

To increase the size of the ramdisk setting:

1. On Citrix XenServer, run the following command:
`xenstore-write /mh/limits/pv-ramdisk-max-size 536,870,912`

2. Confirm the setting is in effect by running `xenstore-ls`.

```
-----  
limits = ""  
pv-kernel-max-size = "33554432"  
pv-ramdisk-max-size = "536,870,912"  
boot-time = ""  
-----
```

3. Remove the pending files left in `/run/xen/pygrub`.



The ramdisk setting returns to the default value after rebooting.

FortiAnalyzer VM upgrade requires more memory

When upgrading FortiAnalyzer VM units from a previous version to FortiAnalyzer 7.2.2 or higher, the upgrade may fail because of memory allocation. As of FortiAnalyzer 7.2.2, FortiAnalyzer VM requires 16 GB of RAM and 4 CPU.

Workaround: Before upgrading FortiAnalyzer VM to FortiAnalyzer 7.2.2, change the memory allocation to 16 GB of RAM.

Maximum ADOM limits for FortiAnalyzer

FortiAnalyzer hardware devices and VMs display a warning when the maximum number of ADOMs is reached. For more details, see [Appendix A - Default and maximum number of ADOMs supported on page 65](#).

Port 8443 reserved

Port 8443 is reserved for https-logging from FortiClient EMS for Chromebooks. See also [FortiAnalyzer 7.0 Ports Reference](#) on the Docs Library.

Hyper-V FortiAnalyzer-VM running on an AMD CPU

A Hyper-V FAZ-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

SSLv3 on FortiAnalyzer-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiAnalyzer-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
    set ssl-protocol t1sv1
end
```

New features

For information about what's new in FortiAnalyzer 7.6.7, see the [FortiAnalyzer 7.6 New Features Guide](#). The [index](#) in the New Features Guide lists new features by release.

Upgrade Information



Prior to upgrading your FortiAnalyzer, please review the FortiAnalyzer Upgrade Guide in detail as it includes all of the necessary steps and associated details required to upgrade your FortiAnalyzer device or VM, including recommended upgrade paths. See the *FortiAnalyzer Upgrade Guide* in the [Fortinet Document Library](#).

This section contains the following topics:

- [Downgrading to previous firmware versions on page 19](#)
- [Firmware image checksums on page 19](#)
- [FortiAnalyzer VM firmware on page 19](#)
- [SNMP MIB files on page 21](#)

Downgrading to previous firmware versions

FortiAnalyzer does not provide a full downgrade path. You can downgrade to a previous firmware release by using the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrade process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset {all-settings | all-except-ip}  
execute format disk
```

Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. After logging in, go to *Download > Firmware Image Checksums*, enter the image file name including the extension, and select *Get Checksum Code*.

FortiAnalyzer VM firmware

Fortinet provides FortiAnalyzer VM firmware images for Amazon AWS, Amazon AWSOnDemand, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

Citrix XenServer and Open Source XenServer

- .out: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- .out.OpenXen.zip: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- .out.CitrixXen.zip: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the Citrix XenServer Virtual Appliance (XVA), Virtual Hard Disk (VHD), and OVF files.

Google Cloud Platform

- .out: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- .out.gcp.zip: Download the 64-bit package for a new FortiAnalyzer VM installation.

Linux KVM

- .out: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- .out.kvm.zip: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example <product>_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip.

- .out: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.

Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, <product>_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip.

- .out: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- .hyperv.zip: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.

Oracle Private Cloud

- .out: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- .out.opc.zip: Download the 64-bit package for a new FortiAnalyzer VM installation.

VMware ESX/ESXi

- .out: Download the 64-bit firmware image to upgrade your existing VM installation.
- .ovf.zip: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information, see the [FortiAnalyzer Data Sheet](#) available on the Fortinet web site. VM installation guides are available in the [Fortinet Document Library](#).

SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiAnalyzer version 5.00 file folder.

Product Integration and Support

This section lists FortiAnalyzer 7.6.7 support of other Fortinet products. It also identifies what FortiAnalyzer features are supported for managed platforms and what languages FortiAnalyzer supports. It also lists which Fortinet models can be managed by FortiAnalyzer.

The section contains the following topics:

- [Supported software on page 22](#)
- [Feature support on page 30](#)
- [Language support on page 31](#)
- [Supported models on page 32](#)

Supported software

FortiAnalyzer 7.6.7 supports the following software:

- [Web browsers on page 23](#)
- [FortiOS and FortiOS Carrier on page 23](#)
- [FortiADC on page 23](#)
- [FortiNDR on page 24](#)
- [FortiAnalyzer on page 24](#)
- [FortiAP on page 24](#)
- [FortiAuthenticator on page 25](#)
- [FortiCache on page 25](#)
- [FortiCASB on page 25](#)
- [FortiClient on page 25](#)
- [FortiDDoS on page 26](#)
- [FortiDeceptor on page 26](#)
- [FortiFirewall and FortiFirewallCarrier on page 26](#)
- [FortiIsolator on page 26](#)
- [FortiMail on page 27](#)
- [FortiManager on page 27](#)
- [FortiNAC on page 27](#)
- [FortiPAM on page 27](#)
- [FortiPortal on page 28](#)
- [FortiProxy on page 28](#)
- [FortiSandbox on page 28](#)
- [FortiSASE on page 28](#)
- [FortiSOAR on page 28](#)

- [FortiSwitch ATCA on page 29](#)
- [FortiToken on page 29](#)
- [FortiWeb on page 29](#)
- [Virtualization on page 29](#)



To confirm that a device model or firmware version is supported by the current firmware version running on FortiAnalyzer, run the following CLI command:
`diagnose dvm supported-platforms list`



Always review the Release Notes of the supported platform firmware version before upgrading your device.

Web browsers

FortiAnalyzer 7.6.7 supports the following web browsers:

- Google Chrome version 144
- Microsoft Edge version 144
- Mozilla Firefox 147

Other web browsers may function correctly, but are not supported by Fortinet.

FortiOS and FortiOS Carrier



The *FortiAnalyzer Release Notes* communicate support for FortiOS versions that are available at the time of the FortiAnalyzer 7.6.7 release. For additional information about other supported FortiOS versions, please refer to the FortiAnalyzer compatibility tool in the [Fortinet Document Library](#).

See [FortiAnalyzer compatibility with FortiOS](#).

FortiAnalyzer 7.6.7 supports the following versions of FortiOS and FortiOS Carrier:

- 7.6.0 to 7.6.7
- 7.4.0 to 7.4.12
- 7.2.0 to 7.2.13
- 7.0.0 to 7.0.19
- 6.4.0 to 6.4.16
- 6.2.0 to 6.2.17

FortiADC

FortiAnalyzer 7.6.7 supports the following versions of FortiADC:

- 8.0.0 and later
- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later
- 7.0.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 6.0.0 and later

FortiNDR

FortiAnalyzer 7.6.7 supports the following versions of FortiNDR:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later
- 7.0.0 and later

FortiAnalyzer

FortiAnalyzer 7.6.7 supports the following versions of FortiAnalyzer:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiAP

FortiAnalyzer 7.6.7 supports the following versions of FortiAP:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later
- 5.6.0 and later
- 5.4.0 and later
- 5.2.0 and later
- 5.0.0 and later

FortiAuthenticator

FortiAnalyzer 7.6.7 supports the following versions of FortiAuthenticator:

- 8.0.0 and later
- 7.0.0 and later
- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 6.3.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 6.0.0 and later

FortiCache

FortiAnalyzer 7.6.7 supports the following versions of FortiCache:

- 4.2.0 and later
- 4.1.0 and later
- 4.0.0 and later

FortiCASB

FortiAnalyzer 7.6.7 supports the following versions of FortiCASB:

- 23.2.0 and later

FortiClient

FortiAnalyzer 7.6.7 supports the following versions of FortiClient:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later

When using FortiClient with FortiAnalyzer, it is recommended to upgrade both to their latest versions. The versions between the two products should match. For example, if using FortiAnalyzer 7.2.0, use FortiClient 7.2.0.

FortiDDoS

FortiAnalyzer 7.6.7 supports the following versions of FortiDDoS:

- 7.2.0 and later
- 7.0.0 and later
- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 6.3.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 5.7.0 and later
- 5.6.0 and later

Limited support. For more information, see [Feature support on page 30](#).

FortiDeceptor

FortiAnalyzer 7.6.7 supports the following versions of FortiDeceptor:

- 6.1.0 and later
- 6.0.0 and later
- 5.3.0 and later
- 5.2.0 and later
- 5.1.0 and later
- 5.0.0 and later
- 4.3.0 and later

FortiFirewall and FortiFirewallCarrier

FortiAnalyzer 7.6.7 supports the following versions of FortiFirewall and FortiFirewallCarrier:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later
- 6.0.0 and later

Fortisolator

FortiAnalyzer 7.6.7 supports the following versions of Fortisolator:

- 2.4.0 and later

FortiMail

FortiAnalyzer 7.6.7 supports the following versions of FortiMail:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later

FortiManager

FortiAnalyzer 7.6.7 supports the following versions of FortiManager:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiNAC

FortiAnalyzer 7.6.7 supports the following versions of FortiNAC:

- 9.4.0 and later
- 9.2.0 and later
- 9.1.0 and later
- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later

FortiPAM

FortiAnalyzer 7.6.7 supports the following versions of FortiPAM:

- 1.8.0 and later
- 1.7.0 and later
- 1.6.0 and later
- 1.5.0 and later
- 1.4.0 and later

- 1.3.0 and later
- 1.2.0 and later
- 1.1.0 and later
- 1.0.0 and later

FortiPortal

For more information about compatibility with FortiPortal, see *FortiPortal Compatibility* in the [Fortinet Document Library](#).

FortiProxy

FortiAnalyzer 7.6.7 supports the following versions of FortiProxy:

- 7.6.0 to 7.6.6
- 7.4.0 to 7.4.13
- 7.2.0 to 7.2.15
- 7.0.0 to 7.0.22
- 2.0.0 to 2.0.5
- 1.2.0 to 1.2.13
- 1.1.0 to 1.1.6
- 1.0.0 to 1.0.7

FortiSandbox

FortiAnalyzer 7.6.7 supports the following versions of FortiSandbox:

- 5.0.0 and later
- 4.4.0 and later
- 4.2.0 and later
- 4.0.0 and later
- 3.2.0 and later

FortiSASE

For more information about compatibility, see the [FortiSASE Release Notes](#).

FortiSOAR

FortiAnalyzer 7.6.7 supports the following versions of FortiSOAR:

- 7.6.0 and later
- 7.5.0 and later
- 7.4.0 and later
- 7.3.0 and later
- 7.2.0 and later

FortiSRA

FortiAnalyzer 7.6.7 supports the following versions of FortiSRA:

- 1.1.0 and later
- 1.0.0 and later

FortiSwitch ATCA

FortiAnalyzer 7.6.7 supports the following versions of FortiSwitch ATCA:

- 5.2.0 and later
- 5.0.0 and later
- 4.3.0 and later

FortiToken

FortiAnalyzer 7.6.7 supports the following versions of FortiToken:

- 3.0.0 and later

FortiAnalyzer supports logs from FortiToken Cloud.

FortiWeb

FortiAnalyzer 7.6.7 supports the following versions of FortiWeb:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiAnalyzer also supports FortiWeb Cloud, including FortiAppSec Cloud.

Virtualization

FortiAnalyzer 7.6.7 supports the following virtualization software:

Public Cloud

- Amazon Web Service AMI, Amazon EC2, Amazon EBS
- Alibaba Cloud
- Google Cloud Platform
- IBM Cloud
- Microsoft Azure
- Oracle Cloud Infrastructure

Private Cloud

- Citrix XenServer 8.2 and later
- OpenSource XenServer 4.2.5
- Microsoft Hyper-V Server 2016, 2019, and 2022
- Nutanix
 - AHV 20220304 and later
 - AOS 6.5 and later
 - NCC 4.6 and later
 - LCM 3.0 and later
- RedHat 9.1
 - Other versions and Linux KVM distributions are also supported
- VMware ESXi versions 6.5 and later

Feature support

The following table lists FortiAnalyzer feature support for log devices.

Platform	Log View	FortiView	Event Management	Reports
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓
FortiADC	✓		✓	✓
FortiAnalyzer	✓		✓	
FortiAP	✓		✓	✓
FortiAuthenticator	✓			
FortiCache	✓		✓	✓
FortiClient registered to FortiGate	✓	✓		✓

Platform	Log View	FortiView	Event Management	Reports
FortiClient registered to FortiClient EMS	✓	✓		✓
FortiDDoS	✓	✓	✓	✓
FortiDeceptor	✓			
FortiFirewall	✓	✓	✓	✓
FortiMail	✓		✓	✓
FortiManager	✓		✓	
FortiNAC	✓			
FortiNDR	✓	✓	✓	✓
FortiPAM	✓		✓	✓
FortiProxy	✓	✓	✓	✓
FortiSandbox	✓		✓	✓
FortiSOAR	✓		✓	✓
FortiSRA	✓		✓	✓
FortiWeb	✓		✓	✓
Syslog	✓		✓	✓

Language support

The following table lists FortiAnalyzer language support information.

Language	GUI	Reports
English	✓	✓
Chinese (Simplified)	✓	✓
Chinese (Traditional)	✓	✓
French	✓	✓
Hebrew		✓
Hungarian		✓
Japanese	✓	✓
Korean	✓	✓

Language	GUI	Reports
Portuguese		✓
Russian		✓
Spanish	✓	✓

To change the FortiAnalyzer language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language on the drop-down menu. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages by exporting a predefined language from FortiAnalyzer, modifying the text to a different language, saving the file as a different language name, and then importing the file into FortiAnalyzer. For more information, see the *FortiAnalyzer Administration Guide*.

Supported models

The following tables list which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch, FortiWeb, FortiCache, FortiProxy, FortiAuthenticator, and other Fortinet product models and firmware versions can send logs to a FortiAnalyzer running version 7.6.7.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

This section contains the following topics:

- [FortiGate models on page 33](#)
- [FortiGate special branch models on page 40](#)
- [FortiCarrier models on page 44](#)
- [FortiCarrier special branch models on page 47](#)
- [FortiADC models on page 49](#)
- [FortiNDR models on page 50](#)
- [FortiAnalyzer models on page 50](#)
- [FortiAP models on page 51](#)
- [FortiAuthenticator models on page 52](#)
- [FortiCache models on page 53](#)
- [FortiDDoS models on page 53](#)
- [FortiDeceptor models on page 53](#)
- [FortiFirewall models on page 54](#)
- [FortiFirewallCarrier models on page 55](#)
- [Fortisolator models on page 56](#)
- [FortiMail models on page 56](#)
- [FortiNAC models on page 56](#)

- [FortiPAM models on page 57](#)
- [FortiProxy models on page 57](#)
- [FortiSandbox models on page 58](#)
- [FortiSOAR models on page 58](#)
- [FortiSwitch ATCA models on page 59](#)
- [FortiWeb models on page 59](#)

FortiGate models

The following FortiGate models are released with FortiOS firmware. For information about supported FortiGate models on special branch releases of FortiOS firmware, see [FortiGate special branch models on page 40](#).

Model	Firmware Version
FortiGate: FortiGate-30G, FortiGate-31G, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50G, FortiGate-50G-5G, FortiGate-50G-DSL, FortiGate-50G-SFP, FortiGate-50G-SFP-POE, FortiGate-51G, FortiGate-51G-5G, FortiGate-51G-SFP-POE, FortiGate-60F, FortiGate-61F, FortiGate-70F, FortiGate-70G, FortiGate-70G-POE, FortiGate-71G, FortiGate-71G-POE, FortiGate-71F, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90G, FortiGate-91G, FortiGate-100F, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-200E, FortiGate-200F, FortiGate-200G, FortiGate-201E, FortiGate-201F, FortiGate-201G, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400F, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-700G, FortiGate-701G, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3600E-DC, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F, FortiGate-4801F-NEBS FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1 FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	7.6

Model	Firmware Version
FortiGate DC: FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-ACDC, FortiGate-3000F-DC, FortiGate-3001F-ACDC, FortiGate-3001F-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3700D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4800F-DC, FortiGate-4801F-DC, FortiGate-4801F-DC-NEBS	
FortiWiFi: FortiWiFi-30G, FortiWiFi-31G, FortiWiFi-40F, FortiWiFi-40F-3G4G, FortiWiFi-50G, FortiWiFi-50G-5G, FortiWiFi-50G-DSL, FortiWiFi-50G-SFP, FortiWiFi-51G, FortiWiFi-60F, FortiWiFi-61F, FortiWiFi-70G, FortiWiFi-70G-POE, FortiWiFi-71G, FortiWiFi-80F-2R, FortiWiFi-81F-2R, FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-POE, FortiWiFi-81F-2R-POE	
FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-Xen	
FortiGate Rugged: FortiGateRugged-50G-5G, FortiGateRugged-60F, FortiGateRugged-60F-3G4G, FortiGateRugged-70F, FortiGateRugged-70F-3G4G, FortiGateRugged-70G, FortiGateRugged-70G-5G-Dual	

Model	Firmware Version
FortiGate: FortiGate-30G, FortiGate-31G, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50G, FortiGate-50G-5G, FortiGate-50G-DSL, FortiGate-50G-SFP, FortiGate-50G-SFP-POE, FortiGate-51G, FortiGate-51G-5G, FortiGate-51G-SFP-POE, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-70G, FortiGate-70G-POE, FortiGate-71F, FortiGate-71G, FortiGate-71G-POE, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100F, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-200G, FortiGate-201E, FortiGate-201F, FortiGate-201G, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400F, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-700G, FortiGate-701G, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3600E-DC, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F, FortiGate-4801F-NEBS FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1 FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC FortiGate DC: FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4801F-DC-NEBS	7.4

Model	Firmware Version
FortiWiFi: FortiWiFi-40F, FortiWiFi-40F-3G4G, FortiWiFi-50G, FortiWiFi-50G-5G, FortiWiFi-50G-DSL, FortiWiFi-50G-SFP, FortiWiFi-51G, FortiWiFi-60E, FortiWiFi-60E-DSL, FortiWiFi-60E-DSLJ, FortiWiFi-60F, FortiWiFi-61E, FortiWiFi-61F, FortiWiFi-70G, FortiWiFi-70G-POE, FortiWiFi-71G, FortiWiFi-80F-2R, FortiWiFi-81F-2R, FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-POE, FortiWiFi-81F-2R-POE FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-Xen FortiGate Rugged: FortiGateRugged-60F, FortiGateRugged-60F-3G4G, FortiGateRugged-70F, FortiGateRugged-70F-3G4G, FortiGateRugged-70G, FortiGateRugged-70G-5G-Dual	
FortiGate: Container-FortiOS, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F, FortiGate-4801F-NEBS FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1 FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	7.2

Model	Firmware Version
FortiGate DC: FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4800F-DC, FortiGate-4801F-DC, FortiGate-4801F-DC-NEBS FortiWiFi: FortiWiFi-60E, FortiWiFi-60E-DSL, FortiWiFi-60E-DSLJ, FortiWiFi-60F, FortiWiFi-61E, FortiWiFi-61F, FortiWiFi-70G, FortiWiFi-71G, FortiWiFi-80F-2R, FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R, FortiWiFi-81F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-POE, FortiWiFi-81F-2R-POE FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FortiOS-VM64, FortiOS-VM64-HV, FortiOS-VM64-KVM, FortiOS-VM64-Xen FortiGate Rugged: FortiGateRugged-60F, FortiGateRugged-60F-3G4G, FortiGateRugged-70F, FortiGateRugged-70F-3G4G	
FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1	7.0

Model	Firmware Version
FortiGate DC: FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC FortiWiFi: FortiWiFi-60E, FortiWiFi-60E-DSL, FortiWiFi-60E-DSLJ, FortiWiFi-60F, FortiWiFi-61E, FortiWiFi-61F, FortiWiFi-80F-2R, FortiWiFi-81F-2R, FortiWiFi-81F-2R-3G4G-POE, FortiWiFi-81F-2R-POE FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FortiOS-VM64, FortiOS-VM64-HV, FortiOS-VM64-KVM, FortiOS-VM64-Xen FortiGate Rugged: FortiGateRugged-60F, FortiGateRugged-60F-3G4G	
FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1	6.4

Model	Firmware Version
FortiGate DC: FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC FortiGate Hardware Low Encryption: FortiGate-100D-LENC FortiWiFi: FortiWiFi-40F, FortiWiFi-40F-3G4G, FortiWiFi-60E, FortiWiFi-60E-DSL, FortiWiFi-60E-DSLJ, FortiWiFi-60F, FortiWiFi-61E, FortiWiFi-61F, FortiWiFi-80F-2R, FortiWiFi-81F-2R, FortiWiFi-81F-2R-3G4G-POE, FortiWiFi-81F-2R-POE FortiGate VM: FortiGate-VM64, FortiGate-VM64-ALL, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FortiOS-VM64, FortiOS-VM64-HV, FortiOS-VM64-KVM, FortiOS-VM64-Xen FortiGate Rugged: FortiGateRugged-60F, FortiGateRugged-60F-3G4G	
FortiGate: FortiGate-30E, FortiGate-30E-3G4G-GBL, FortiGate-30E-3G4G-INTL, FortiGate-30E-3G4G-NAM, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50E, FortiGate-51E, FortiGate-52E, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-80D, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-92D, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140D, FortiGate-140D-POE, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201F, FortiGate-201E, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3600E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1	6.2

Model	Firmware Version
FortiGate DC: FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-2201E-ACDC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC	
FortiGate Hardware Low Encryption: FortiGate-100D-LENC	
FortiWiFi: FortiWiFi-30E, FortiWiFi-30E-3G4G-INTL, FortiWiFi-30E-3G4G-NAM, FortiWiFi-40F, FortiWiFi-40F-3G4G, FortiWiFi-50E, FortiWiFi-50E-2R, FortiWiFi-51E, FortiWiFi-60E, FortiWiFi-60E-DSL, FortiWiFi-60E-DSLJ, FortiWiFi-60F, FortiWiFi-61E, FortiWiFi-61F, FortiWiFi-80F-2R, FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R, FortiWiFi-81F-2R-POE	
FortiGate VM: FortiGate-VM64, FortiGate-VM64-ALL, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AWSONDEMAND, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager	
FortiOS-VM: FortiOS-VM64, FortiOS-VM64-HV, FortiOS-VM64-KVM, FortiOS-VM64-Xen	
FortiGate Rugged: FortiGateRugged-30D, FortiGateRugged-35D, FortiGateRugged-60F, FortiGateRugged-60F-3G4G, FortiGateRugged-90D	

FortiGate special branch models

The following FortiGate models are released on special branches of FortiOS. FortiAnalyzer version 7.6.7 supports these models on the identified FortiOS version and build number.

For information about supported FortiGate models released with FortiOS firmware, see [FortiGate models on page 33](#).

FortiGate Model	FortiOS Version
FortiGate-400G	7.6.6
FortiGate-401G	7.6.6
FortiGate-3000G, FortiGate-3001G	7.6.6

FortiOS 7.4

FortiGate Model	FortiOS Version
FortiGate-70G-POE-5G, FortiGate-71G-POE-5G	7.4.8
FortiGate-3800G, FortiGate-3801G FortiGate-3800G-DC, FortiGate-3801G-DC	7.4.11
FortiGateRugged-50G-5G	7.4.8
FortiGateRugged-60G, FortiGateRugged-60G-5G, FortiGateRugged-60G-5G-M12, FortiGateRugged-60G-M12	7.4.11
FortiGateRugged-70G-5G	7.4.11

FortiOS 7.2

FortiGate Model	FortiOS Version
FortiGate-30G, FortiGate-31G	7.2.12
FortiGate-70G	7.2.11
FortiGate-71G	7.2.12
FortiGate-70G-POE	7.2.12
FortiGate-71G-POE	7.2.11
FortiGate-200G, FortiGate-201G	7.2.12
FortiGate-700G, FortiGate-701G	7.2.11
FortiWiFi-30G, FortiWiFi-31G	7.2.12
FortiWiFi-70G, FortiWiFi-70G-POE, FortiWiFi-71G	7.2.11

FortiOS 7.0

FortiGate Model	FortiOS Version
FortiGate-50G, FortiGate-50G-5G, FortiGate-50G-DSL, FortiGate-50G-SFP, FortiGate-50G-SFP-POE	7.0.17
FortiGate-51G, FortiGate-51G-5G, FortiGate-51G-SFP-POE	7.0.17
FortiGate-80F-DSL	7.0.17
FortiGate-90G, FortiGate-91G	7.0.17
FortiGate-120G, FortiGate-121G	7.0.16
FortiGate-900G, FortiGate-900G-DC	7.0.17

FortiGate Model	FortiOS Version
FortiGate-901G, FortiGate-901G-DC	
FortiGate-1000F, FortiGate-1001F	7.0.17
FortiGate-3200F, FortiGate-3201F	7.0.17
FortiGate-3700F, FortiGate-3701F	7.0.17
FortiGate-4800F, FortiGate-4800F-DC	7.0.17
FortiGate-4801F, FortiGate-4801F-DC, FortiGate-4801F-NEBS, FortiGate-4801F-DC-NEBS	
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	7.0.16
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	7.0.16
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	7.0.16
FortiGateRugged-50G-5G	7.0.17
FortiGateRugged-70F, FortiGateRugged-70F-3G4G	7.0.17
FortiGateRugged-70G	7.0.15
FortiGateRugged-70G-5G-Dual	7.0.16
FortiWiFi-50G, FortiWiFi-50G-5G, FortiWiFi-50G-DSL, FortiWiFi-50G-SFP	7.0.17
FortiWiFi-51G	7.0.17
FortiWiFi-51G-5G	7.0.15
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	7.0.17

FortiOS 6.4

FortiGate Model	FortiOS Version
FortiGate-400F, FortiGate-401F, FortiGate-400F-DC, FortiGate-401F-DC	6.4.13
FortiGate-600F, FortiGate-601F	6.4.13
FortiGate-3500F	6.4.6
FortiGate-3501F	6.4.6
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	6.4.13

FortiGate Model	FortiOS Version
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	6.4.13
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	6.4.13
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	6.4.7

FortiOS 6.2

FortiGate Model	FortiOS Version
FortiGate-1800F, FortiGate-1800F-DC FortiGate-1801F, FortiGate-1801F-DC	6.2.9
FortiGate-2600F, FortiGate-2600F-DC FortiGate-2601F, FortiGate-2601F-DC	6.2.9
FortiGate-4200F, FortiGate-4200F-DC FortiGate-4201F, FortiGate-4201F-DC	6.2.9
FortiGate-4400F, FortiGate-4400F-DC FortiGate-4401F, FortiGate-4401F-DC	6.2.9
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	6.2.13
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	6.2.13
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	6.2.6

FortiOS 6.0

FortiGate Model	FortiOS Version
FortiGate-30E-3G4G-GBL	6.0
FortiGate-40F, FortiGate-40F-3G4G	6.0
FortiGate-41F	6.0.6
FortiGate-41F-3G4G	6.0.6
FortiGate-60F, FortiGate-61F	6.0
FortiGate-100F, FortiGate-101F	6.0

FortiGate Model	FortiOS Version
FortiGate-1100E, FortiGate-1100E-DC, FortiGate-1101E	6.0
FortiGate-1800F, FortiGate-1800F-DC FortiGate-1801F, FortiGate-1801F-DC	6.0
FortiGate-2200E, FortiGate-2201E, FortiGate-2201E-ACDC	6.0
FortiGate-3300E, FortiGate-3301E	6.0
FortiWiFi-40F, FortiWiFi-40F-3G4G	6.0
FortiWiFi-41F	6.0.6
FortiWiFi-41F-3G4G	6.0.6
FortiWiFi-60F, FortiWiFi-61F	6.0

FortiCarrier models

The following FortiCarrier models are released with FortiCarrier firmware.

For information about supported FortiCarrier models on special branch releases of FortiCarrier firmware, see [FortiCarrier special branch models on page 47](#).

Model	Firmware Version
FortiCarrier: FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F, FortiCarrier-4801F-NEBS FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3000F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4800F-DC, FortiCarrier-4801F-DC, FortiCarrier-4801F-DC-NEBS	7.6

Model	Firmware Version
FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	
FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F, FortiCarrier-4801F-NEBS FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4801F-DC-NEBS FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-IBM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	7.4
FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F, FortiCarrier-4801F-NEBS FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1	7.2

Model	Firmware Version
FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4801F-DC-NEBS FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	
FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen, FortiCarrier-ARM64-KVM	7.0
FortiCarrier: FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1	6.4

Model	Firmware Version
FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC FortiCarrier-VM: FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	
FortiCarrier: FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC FortiCarrier 6K and 7K: FortiCarrier-6000F, FortiCarrier-6300F, FortiCarrier-6301F, FortiCarrier-6500F, FortiCarrier-6501F, FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7000F, FortiCarrier-7121F, FortiCarrier-7121F-2 FortiCarrier 6K and 7K DC: FortiCarrier-6000F-DC, FortiCarrier-6300F-DC, FortiCarrier-6301F-DC, FortiCarrier-6500F-DC, FortiCarrier-6501F-DC, FortiCarrier-7060E-8-DC, FortiCarrier-7121F-DC, FortiCarrier-7121F-2-DC FortiCarrier-VM: FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	6.2

FortiCarrier special branch models

The following FortiCarrier models are released on special branches of FortiOS Carrier. FortiAnalyzer version 7.6.7 supports these models on the identified FortiOS Carrier version and build number.

For information about supported FortiCarrier models released with FortiOS Carrier firmware, see [FortiCarrier models on page 44](#).

FortiCarrier 7.4

FortiCarrier Model	FortiCarrier Version
FortiCarrier-3800G, FortiCarrier-3801G	7.4.11
FortiCarrier-3800G-DC, FortiCarrier-3801G-DC	

FortiCarrier 7.0

FortiCarrier Model	FortiCarrier Version
FortiCarrier-3200F, FortiCarrier-3201F	7.0.17
FortiCarrier-3700F, FortiCarrier-3701F	7.0.17
FortiCarrier-4800F, FortiCarrier-4800F-DC FortiCarrier-4801F, FortiCarrier-4801F-DC, FortiCarrier-4801F-NEBS, FortiCarrier-4801F-DC-NEBS	7.0.17
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	7.0.16
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	7.0.16
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	7.0.16

FortiCarrier 6.4

FortiCarrier Model	FortiCarrier Version
FortiCarrier-3500F	6.4.6
FortiCarrier-3501F	6.4.6
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	6.4.13
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	6.4.13
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	6.4.13

FortiCarrier 6.2

FortiCarrier Model	FortiCarrier Version
FortiCarrier-4200F, FortiCarrier-4200F-DC	6.2.9

FortiCarrier Model	FortiCarrier Version
FortiCarrier-4201F, FortiCarrier-4201F-DC FortiCarrier-4400F, FortiCarrier-4400F-DC, FortiCarrier-4401F, FortiCarrier-4401F-DC	
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	6.2.13
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	6.2.13

FortiCarrier 6.0

FortiCarrier Model	FortiCarrier Version
FortiCarrier-VM64-Azure	6.0

FortiADC models

Model	Firmware Version
FortiADC: FortiADC-1000G, FortiADC-2000G, FortiADC-4000G, FortiADC-5000G	8.0
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-320F, FortiADC-400F, FortiADC-420F, FortiADC-1000F, FortiADC-1200F, FortiADC-2000F, FortiADC-2200F, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F FortiADC VM: FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVER, FortiADC-VM	7.6
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-320F, FortiADC-400D, FortiADC-400F, FortiADC-420F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F	7.4

Model	Firmware Version
FortiADC VM: FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVER, FortiADC-VM	
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-400D, FortiADC-400F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F	6.2, 7.0, 7.1, 7.2
FortiADC VM: FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVER, FortiADC-VM	

FortiNDR models

Model	Firmware Version
FortiNDR: FortiNDR-1000F, FortiNDR-2500G, FortiNDR-3500F, FortiNDR-3600G FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM, FortiNDR-VMC	7.4, 7.6
FortiNDR: FortiNDR-1000F, FortiNDR-3500F FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM	7.2
FortiNDR: FortiNDR-3500F FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM	7.0, 7.1

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FortiAnalyzer-300G, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3750G, FortiAnalyzer-3900E, FortiAnalyzer-K8S-CLOUD FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-KVM-CLOUD, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-VIO-CLOUD, FortiAnalyzer-VM64-Xen	7.6

Model	Firmware Version
FortiAnalyzer: FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3750G, FortiAnalyzer-3900E, FortiAnalyzer-K8S-CLOUD FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-KVM-CLOUD, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-VIO-CLOUD, FortiAnalyzer-VM64-Xen	7.4
FortiAnalyzer: FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E, FortiAnalyzer-K8S-CLOUD FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-KVM-CLOUD, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-VIO-CLOUD, FortiAnalyzer-VM64-Xen	7.2
FortiAnalyzer: FortiAnalyzer-200F, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E, FortiAnalyzer-K8S-CLOUD FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-ALI-OnDemand, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-GCP-OnDemand, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-KVM-CLOUD, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-VIO-CLOUD, FortiAnalyzer-VM64-Xen	7.0

FortiAP models

Model	Firmware Version
FortiAP-231FL, FortiAP-231K, FortiAP-241K, FortiAP-243K, FortiAP-431FL, FortiAP-432FR, FortiAP-432G, FortiAP-433FL, FortiAP-441K, FortiAP-443K	7.4

Model	Firmware Version
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-231G, FortiAP-233G, FortiAP-234F, FortiAP-234G, FortiAP-431F, FortiAP-431G, FortiAP-432F, FortiAP-432G, FortiAP-433F, FortiAP-433G, FortiAP-831F	7.2
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-234F, FortiAP-431F, FortiAP-432F, FortiAP-433F, FortiAP-831F	7.0
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-234F, FortiAP-321E, FortiAP-421E, FortiAP-423E, FortiAP-431F, FortiAP-432F, FortiAP-433F, FortiAP-831F, FortiAP-S221E, FortiAP-S223E, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E	6.4
FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-231E, FortiAP-321E, FortiAP-421E, FortiAP-423E, FortiAP-S221E, FortiAP-S223E, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E	6.2
FortiAP-11C, FortiAP-14C, FortiAP-21B, FortiAP-21D, FortiAP-22B, FortiAP-24D, FortiAP-25D, FortiAP-28C, FortiAP-112B, FortiAP-112D, FortiAP-214B, FortiAP-221B, FortiAP-221C, FortiAP-221E, FortiAP-222, FortiAP-222C, FortiAP-222E, FortiAP-223B, FortiAP-223C, FortiAP-223E, FortiAP-224D, FortiAP-224E, FortiAP-231E, FortiAP-320B, FortiAP-320C, FortiAP-321C, FortiAP-321CR, FortiAP-321E, FortiAP-322CR, FortiAP-323CR, FortiAP-421E, FortiAP-423E, FortiAP-C23JD, FortiAP-C24JE, FortiAP-C220C, FortiAP-C225C, FortiAP-S221E, FortiAP-S223E, FortiAP-S311C, FortiAP-S313C, FortiAP-S321C, FortiAP-S322C, FortiAP-S323C, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E, FortiAP-U24JEV, FortiAP-U221EV, FortiAP-U223EV, FortiAP-U231F, FortiAP-U231G, FortiAP-U234F, FortiAP-U321EV, FortiAP-U323EV, FortiAP-U421EV, FortiAP-U422EV, FortiAP-U423EV, FortiAP-U431F, FortiAP-U432F, FortiAP-U433F	6.0

FortiAuthenticator models

Model	Firmware Version
FortiAuthenticator VM: FAC-VM	7.0, 8.0
FortiAuthenticator: FAC-200E, FAC-300F, FAC-400E, FAC-800F, FAC-2000E, FAC-3000E, FAC-3000F FortiAuthenticator VM: FAC-VM	6.5, 6.6
FortiAuthenticator: FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E, FAC-3000F FortiAuthenticator VM: FAC-VM	6.4
FortiAuthenticator: FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E FortiAuthenticator VM: FAC-VM	6.0, 6.1, 6.2, 6.3

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3000E, FCH-3900E FortiCache VM: FCH-KVM, FCH-VM64	4.1, 4.2
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E FortiCache VM: FCH-VM64	4.0

FortiDDoS models

Model	Firmware Version
FortiDDoS: FortiDDoS-3000G, FortiDDoS-4000G	7.2
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-1500G, FortiDDoS-1500G-LR, FortiDDoS-2000F, FortiDDoS-2000G, FortiDDoS-3000F, FortiDDoS-3000G FortiDDoS VM: FortiDDoS-VM	7.0
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	6.4, 6.5, 6.6
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F FortiDDoS VM: FortiDDoS-VM	6.3
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F FortiDDoS VM: FortiDDoS-VM	6.2
FortiDDoS: FortiDDoS-200B, FortiDDoS-400B, FortiDDoS-600B, FortiDDoS-800B, FortiDDoS-900B, FortiDDoS-1000B, FortiDDoS-1200B, FortiDDoS-1500E, FortiDDoS-2000B, FortiDDoS-2000E	5.6, 5.7

FortiDeceptor models

Model	Firmware Version
FortiDeceptor: FDC-100G, FDC-1000F, FDC-1000G FortiDeceptor Rugged: FDCR-100G FortiDeceptor VM: FDC-VM	5.0, 5.1, 5.2, 5.3, 6.0, 6.1
FortiDeceptor: FDC-1000F, FDC-1000G FortiDeceptor Rugged: FDCR-100G FortiDeceptor VM: FDC-VM	4.3

FortiFirewall models

Some of the following FortiFirewall models are released on special branches of FortiFirewall firmware. FortiAnalyzer version 7.6.7 supports these models on the identified FortiFirewall firmware version and build number.

Model	Firmware Version
FortiFirewall: FortiFirewall-1801F, FortiFirewall-2600F, FortiFirewall-3001F, FortiFirewall-3501F, FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F, FortiFirewall-4801F-NEBS FortiFirewall DC: FortiFirewall-3001F-DC, FortiFirewall-3980E-DC, FortiFirewall-4200F-DC, FortiFirewall-4400F-DC, FortiFirewall-4401F-DC, FortiFirewall-4801F-DC-NEBS FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.6
FortiFirewall: FortiFirewall-1801F, FortiFirewall-2600F, FortiFirewall-3001F, FortiFirewall-3501F, FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F, FortiFirewall-4801F-NEBS FortiFirewall DC: FortiFirewall-3001F-DC, FortiFirewall-3980E-DC, FortiFirewall-4200F-DC, FortiFirewall-4400F-DC, FortiFirewall-4401F-DC, FortiFirewall-4801F-DC-NEBS FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.4
FortiFirewall: FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F, FortiFirewall-4801F-NEBS FortiFirewall DC: FortiFirewall-4200F-DC, FortiFirewall-4401F-DC, FortiFirewall-4801F-DC-NEBS FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.2
FortiFirewall: FortiFirewall-3980E FortiFirewall DC: FortiFirewall-3980E-DC FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.0

FortiFirewall special branch models

Model	Firmware Version	Firmware Build (for special branch)
FortiFirewall: FortiFirewall-3001F FortiFirewall DC: FortiFirewall-3001F-DC,	7.0.10	4955
FortiFirewall: FortiFirewall-3501F FortiFirewall DC: FortiFirewall-3001F-DC,	7.0.10	4955

FortiFirewallCarrier models

Some of the following FortiFirewallCarrier models are released on special branches of FortiFirewallCarrier firmware. FortiAnalyzer version 7.6.7 supports these models on the identified FortiFirewallCarrier firmware version and build number.

Model	Firmware Version
FortiFirewallCarrier: FortiFirewallCarrier-3001F, FortiFirewallCarrier-3501F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4401F, FortiFirewallCarrier-4801F, FortiFirewallCarrier-4801F-NEBS FortiFirewallCarrier DC: FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4401F-DC, FortiFirewallCarrier-4801F-DC-NEBS FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.6
FortiFirewallCarrier: FortiFirewallCarrier-1801F, FortiFirewallCarrier-2600F, FortiFirewallCarrier-3001F, FortiFirewallCarrier-3501F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4401F, FortiFirewallCarrier-4801F, FortiFirewallCarrier-4801F-NEBS FortiFirewallCarrier DC: FortiFirewallCarrier-1801F-DC, FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4401F-DC, FortiFirewallCarrier-4801F-DC-NEBS FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.4
FortiFirewallCarrier: FortiFirewallCarrier-2600F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4801F, FortiFirewallCarrier-4801F-NEBS FortiFirewallCarrier DC: FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4801F-DC-NEBS FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.2
FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.0

FortiFirewall special branch models

Model	Firmware Version	Firmware Build
FortiFirewallCarrier: FortiFirewallCarrier-1801F, FortiFirewallCarrier-4401F	7.2.6	4609
FortiFirewallCarrier: FortiFirewallCarrier-3001F	7.0.10	4955
FortiFirewallCarrier: FortiFirewallCarrier-3501F	7.0.10	4940

Fortisolator models

Model	Firmware Version
Fortisolator: Fortisolator-1000F, Fortisolator-1000G, Fortisolator-3000F	2.4
Fortisolator-VM: Fortisolator-VM	

FortiMail models

Model	Firmware Version
FortiMail: FE-60D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-900G, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.6
FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN, FortiMail Cloud	
FortiMail: FE-60D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.4
FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN	
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.2
FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN	
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-1000D, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.0
FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN	
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-1000D, FE-2000E, FE-3000D, FE-3000E, FE-3200E	6.2, 6.4
FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN, FortiMail Cloud	

FortiNAC models

Model	Firmware Version
FortiNAC: FortiNAC-500, FortiNAC-600, FortiNAC-700, FortiNAC-C-1000C, FortiNAC-C-2000C, FortiNAC-CA-500C, FortiNAC-Manager-550	9.4
FortiNAC VM: FortiNAC-C-VM, FortiNAC-CA-VM, FortiNAC-M-VM	

Model	Firmware Version
FortiNAC: FortiNAC-500, FortiNAC-600, FortiNAC-700, FortiNAC-C-1000C, FortiNAC-C-2000C, FortiNAC-Manager-550 FortiNAC VM: FortiNAC-C-VM, FortiNAC-CA-VM, FortiNAC-M-VM	9.1, 9.2
FortiNAC: FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F FortiNAC VM: FortiNAC-VM-ESXI	7.6
FortiNAC: FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F FortiNAC VM: FortiNAC-VM-ESXI, FortiNAC-MX-VM	7.4
FortiNAC: FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F FortiNAC VM: FortiNAC-F-VM, FortiNAC-VM-ESXI, FortiNAC-MX-VM	7.2

FortiPAM models

Model	Firmware Version
FortiPAM: FortiPAM-100G, FortiPAM-400G, FortiPAM-1000G, FortiPAM-1100G, FortiPAM-3000G, FortiPAM-3100G FortiPAM VM: FortiPAM-Azure, FortiPAM-KVM	1.7, 1.8
FortiPAM: FortiPAM-1000G, FortiPAM-3000G FortiPAM VM: FortiPAM-Azure, FortiPAM-KVM	1.5, 1.6
FortiPAM: FortiPAM-1000G, FortiPAM-3000G FortiPAM VM: FortiPAM-AWS, FortiPAM-Azure, FortiPAM-GCP, FortiPAM-HyperV, FortiPAM-KVM, FortiPAM-VM64	1.0, 1.1, 1.2, 1.3, 1.4

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.6
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.4
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G	7.2

Model	Firmware Version
FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-VM64	
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.0
FortiProxy: FPX-400E, FPX-2000E, FPX-4000E FortiProxy VM: FortiProxy-KVM, FortiProxy-VM64	1.0, 1.1, 1.2, 2.0

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-500F, FSA-500G, FSA-1000F, FSA-1500G, FSA-2000E, FSA-3000E, FSA-3000F FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FSA-AliCloud, FSA-AliCloud-Nested, FSA-AWS, FSA-AWS-Nested, FSA-Azure, FSA-Azure-Nested, FSA-Cloud, FSA-GCP, FSA-GCP-Nested, FSA-HYPERV, FSA-KVM, FSA-OCI-Nested, FSA-VM	5.0
FortiSandbox: FSA-500F, FSA-500G, FSA-1000D, FSA-1000F, FSA-1500G, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FSA-AWS, FSA-Cloud, FSA-VM	4.2, 4.4
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FSA-AWS, FSA-Cloud, FSA-VM	4.0
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FSA-AWS, FSA-VM	3.2

FortiSOAR models

Model	Firmware Version
FortiSOAR VM: FortiSOAR-VM	7.2, 7.3, 7.4, 7.5, 7.6

FortiSRA models

Model	Firmware Version
FortiSRA: FortiSRA-1000G, FortiSRA-3000G	1.0, 1.1
FortiSRA-VM: FortiSRA-Azure, FortiSRA-HyperV, FortiSRA-KVM, FortiSRA-VM64	

FortiSwitch ATCA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	5.2
FortiSwitch: FS-5003A, FS-5003B	5.0
FortiController: FTCL-5103B	
FortiSwitch: FS-5003A, FS-5003B	4.3

FortiWeb models

Model	Firmware Version
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-100F, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-400F, FortiWeb-600D, FortiWeb-600E, FortiWeb-600F, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer FortiWeb Cloud , including FortiAppSec Cloud.	7.6
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-100F, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-400F, FortiWeb-600D, FortiWeb-600E, FortiWeb-600F, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer FortiWeb Cloud , including FortiAppSec Cloud.	7.4

Model	Firmware Version
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer FortiWeb Cloud , including FortiAppSec Cloud.	7.2
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer FortiWeb Cloud , including FortiAppSec Cloud.	7.0

Resolved issues

The following issues have been fixed in 7.6.7. To inquire about a particular bug, please contact [Customer Service & Support](#).

Device Manager

Bug ID	Description
1227977	Adding FortiSASE devices results in error The device's serial number does not match database.

Event Management

Bug ID	Description
1275382	The webhook for the event handler is still being triggered even though it was already suppressed.

Log View

Bug ID	Description
1198027	No results are returned when filtering the Event Message column by a suggested value that contains a comma.

Others

Bug ID	Description
1217641	The output of diagnose fortilogd logvol-adom is not correct.
1291787	The field names are not mapped correctly when log forwarding is configured in CEF mode.

Reports

Bug ID	Description
1224929	Following the upgrade, the data shown in the VPN reports Top 5 Site-to-Site IPsec Tunnels by Bandwidth chart appears to be inaccurate.

System Settings

Bug ID	Description
1128305	The forwarding rate is not zero when the log forwarding server is disabled or not configured.
1220686	SAML SSO synchronization prevents admin SSO login after HA failover.

Known issues

Known issues are organized into the following categories:

- [New known issues](#)
- [Existing known issues](#)

To inquire about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

New known issues

No new issues have been identified in version 7.6.7.

Existing known issues

The following issues have been identified in a previous version of FortiAnalyzer and remain in FortiAnalyzer 7.6.7.

Fabric View

Bug ID	Description
1231421	Playbook fail to run for downstream FortiGates in Security Fabric.
1236262	FortiOS Connector does not appear under the correct Security Fabric name.

FortiSoC

Bug ID	Description
1202951	Outbreak Alerts page displays the report list is unavailable in FortiGuard despite valid license and connectivity.

FortiView

Bug ID	Description
1092311	FortiAnalyzer may not display any data when accessing FortiView in the VPN site-to-site tab.

Others

Bug ID	Description
1098690	After an upgrade, users (prior to the upgrade) who were created and assigned to a custom admin profile (with the super_user_profile enabled) may encounter a GUI issue. Upon successful login, the login prompt disappears, but only the background color remains visible, with no additional GUI elements loaded.

Reports

Bug ID	Description
1127015	FortiAnalyzer report charts are shifted if Print Orientation is set to "Portrait".

System Settings

Bug ID	Description
1142016	The <i>Index Fetched Logs</i> feature in <i>Request Fetch under Advanced > Log Fetch</i> is not functioning as expected.

Appendix A - Default and maximum number of ADOMs supported

This section identifies the supported number of ADOMs for FortiAnalyzer hardware models and virtual machines.



When operating as a Fabric supervisor, FortiAnalyzer does not count member ADOMs and devices toward its license limit.

See also the [FortiAnalyzer Data Sheet](#).

Hardware models

FortiAnalyzer supports a default number of ADOMs based on hardware model.

Some hardware models support an ADOM subscription license. When you purchase an ADOM subscription license, you increase the number of supported ADOMs. For example, you can purchase an ADOM subscription license for the FAZ-3000G series, which allows you to use up to a maximum of 1200 ADOMs. Other hardware models do not support the ADOM subscription license.

Some older hardware models do not enforce ADOM limits. These models will display a warning message when the ADOM limit is reached or exceeded; adding more ADOMs may affect performance. These devices are still subject to maximum device limits which are listed in the FortiAnalyzer Data Sheet.

The table below lists the maximum number of ADOMs by platform. Models that enforce the maximum as a hard limit are indicated in the *Hard limit* column.

FortiAnalyzer Platform	Maximum number of ADOMs	Hard limit
Desktop models	1	✓
150G	3	✓
300G	25	✓
800G and 810G	50	✓
1000F	50	✓
1000G	50	✓
2000E	250	

FortiAnalyzer Platform	Maximum number of ADOMs	Hard limit
3000F	500	
3000G and 3100G	500 *1200	✓
3500F	500	
3500G and 3510G	500 *10000	✓
3700F	1200	
3700G and 3750G	1200 *10000	✓

*Maximum number of supported ADOMs can be increased to this value with an ADOM subscription license.

Virtual Machines



ADOM limits are recommended for VMs, but not enforced.

FortiAnalyzer-VM subscription licenses are stackable and come in the following tiers:

- 5 GB/Day
- 50 GB/Day
- 500 GB/Day

The default number of ADOMs is based on the total GB/Day licensed for the FortiAnalyzer platform.

See the table below for the default maximum number of ADOMs supported according to GB/Day:

Licensed GB/Day	Default number of ADOMs
5 GB/Day	10
5 GB/Day < License ≤ 25 GB/Day	25
25 GB/Day < License ≤ 100 GB/Day	50
100 GB/Day < License ≤ 500 GB/Day	250
500 GB/Day < License ≤ 1000 GB/Day	500
1000 GB/Day < License ≤ 5000 GB/Day	800
License > 5000 GB/Day	1200



Example:

The 5 GB/Day license includes 10 ADOMs.

When two 5 GB/Day licenses are stacked, only the GB/Day is stacked (5 GB/Day + 5 GB/Day = 10 GB/Day). The default number of ADOMs, however, is not stacked. Instead, the default number of ADOMs is increased based on the total GB/Day licensed to the FortiAnalyzer-VM. Referring to the table above, a FortiAnalyzer-VM licensed for 10 GB/Day will include 25 ADOMs.



www.fortinet.com

Copyright© 2026 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's Chief Legal Officer, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.